

EVEREADY®

LED PIR FLOODLIGHT



 IEE WIRING REGULATION BS7671	 TOOLS NEEDED	 SCREWS NEEDED (NOT SUPPLIED)	 DRILL	 3 WIRE INCOMING	 CLASS I
 CHECK FOR CONCEALED PIPES / CABLES	 SUPPLY VOLTAGE 240V 50Hz	 1.8 - 2.5m GROUND CLEARANCE	 SHELTERED POSITIONING	 MOUNTING SURFACE	 OUTDOOR USE ONLY

GB IMPORTANT Installation must be installed by a qualified electrician (BS7671).
FR IMPORTANT! L'installation doit être effectuée par un électricien qualifié (BS7671).
DE WICHTIG! Die Installation sollte von einem qualifizierten Elektriker durchgeführt werden (BS7671).
IT IMPORTANTE! L'installazione deve essere effettuata da un elettricista qualificato (BS7671).
ES ¡IMPORTANTE! La instalación debe ser realizada por un electricista autorizado (BS7671).
PT INFORMAÇÃO IMPORTANTE A instalação deve ser feita por um electricista profissional.
NL BELANGRIJK! Laat de installatie uitvoeren door een electricien.
SE VIKTIGT! Installationen skall utföras av en behörig elektriker.
NO IVIKTIG! Installasjonen skal utføres av en behörig elektriker.
DK VIGTIGT! Installationen skal foretages af en elektriker.
FI TÄRKEÄÄ! Asennuksen saa tehdä vain valtuutettu sähköasentaja.

1

2

3

4

5

INCOMING SUPPLY

H05RN-F 3 x 1.0mm² waterproof cable Product MUST be earthed

LIVE (Brown or Red) ——— LIVE - Brown

EARTH (Green & Yellow) ——— EARTH - Green & Yellow

NEUTRAL (Blue or Black) ——— NEUTRAL - Blue

Pre wired cable does NOT include connector. Once wired you must ensure that the connection is waterproof via a suitable IP rated connection box or with an adequate amount of insulation tape and located in a sheltered position.

TO FITTING

TIME

Anti-Clockwise/Left ← LUX → Clockwise/Right

Turning the dial to the MOON will programme the sensor to ONLY work at NIGHT

Turning the dial to the SUN will programme the sensor to work at DAY & NIGHT (Constant)

In-between these 2 extremes reflect the LUX level when the sensor will function – eg DUSK



© 2020 Energizer. Eveready and certain graphic designs are trademarks of Energizer Brands, LLC and related subsidiaries and are used under license by Supreme Imports Ltd. All other brand names are trademarks of their respective owners. Neither Supreme Imports Ltd nor Energizer Brands, LLC is affiliated with the respective owners of their trademarks.



PIR Max Switch - 50W Total (max)				
Flood	10W	20W	30W	50W
Additional	40W	30W	20W	-
Total	50W	50W	50W	50W