## **User Manual of High Bay**

Product Introduction:	Technica	I Paramet	ers:					
Welcome to purchase our led high bay light, which is with imported	Product/Parameter	100W/150W	200W	240W	300W	400W	500W	600W
high-brightness SMD2835 led chip, with unique high purity die-cast aluminum heat	Input Voltage AC100-277V;EU-Standard (Lifud):AC220-240V AC100-277V							
sink, and high effeciency constant current or constant voltage driver. Ideal product for	Power Frequency 50/60Hz							
the factories, Stadiums, gas stations, train stations, and similar applications	Material			ŀ	ADC12 aluminum			
, , <b>5</b> , , , , , , , , , , , , , , , , , , ,	Driver		lifud/sosen			SOS	en	
	Working Temperature				-30°C~50°C			
Product Features:	Storing Temperature				-40°C~65°C			
1 The meterial of best sink is high thermal conductivity dis east aluminum good for best	Working Humidity Beam Angle		60°/00°/400°		15%~95% RH	120	•	
1 The material of heat sink is high thermal conductivity die-cast aluminum, good for heat dissipation and the surface is anti-static.	Color Temperature		60°/90°/120°	4000	/ 5000K/5700K/65</td <td></td> <td></td> <td></td>			
	Net Weight	2.2kg±0.3	2.4kg±0.3	3.1kg±0.3	5.5kg±0.5	6.2kg±0.5	9.45kg±0.8	14.6kg±0.8
2. Multiple power, beam angle, installation methods, and accessories are available for selection.	Lamp Dimension	φ260*125mm	φ260*145mm	φ260*146mm	φ320*150mm	φ320*182mm	φ375*196mm	φ375*224mm
3.This fixture is waterproof,dustproof,anticorrosive. Warning:	Packing inclu 1.1pcs LED hi 2.1pcs produc	gh bay light.	al.	1				
1.please read the manual carefully before installation	3.1pcs installa							
	Wiring D	iagram:						
2. 🖄 caution, electricshockrisk	AC cord	5			0_10V d	immable		
					0-10v u	iiiiiabie		
3. The luminaire must be installed by qualified electrician in accordance with local rules and codes.								
4.The external flexible cable or cord of this luminaire cannot be replaced; if the cord is damaged,	EU- Standard	US-Standard	— , n , <b> ( - )</b> , [	label	purple	DIM+		label
4.The external flexible cable or cord of this luminaire cannot be replaced; if the cord is damaged, the luminaire shall be destroyed	EU- Standard brown	black 🗕		LL	purple	DIM+		D+ D+
<ul> <li>4.The external flexible cable or cord of this luminaire cannot be replaced; if the cord is damaged, the luminaire shall be destroyed</li> <li>5.please keep the fixture out of fire,electric shock,vibration</li> </ul>	EU- Standard brown blue	black 🗕		L L N N	Pink	DIM-		D+ D+ D- D-
4.The external flexible cable or cord of this luminaire cannot be replaced; if the cord is damaged, the luminaire shall be destroyed	EU- Standard brown blue	black 🗕		LL		DIM-	V	D+ D+
<ul> <li>4.The external flexible cable or cord of this luminaire cannot be replaced; if the cord is damaged, the luminaire shall be destroyed</li> <li>5.please keep the fixture out of fire,electric shock,vibration</li> <li>6.The regular sensor could not be used with Emgergy Driver at the same time.If the sensor should</li> </ul>	EU- Standard brown blue	black 🗕		L L N N	Pink	DIM-		D+ D+ D- D-
<ul> <li>4. The external flexible cable or cord of this luminaire cannot be replaced; if the cord is damaged, the luminaire shall be destroyed</li> <li>5. please keep the fixture out of fire, electric shock, vibration</li> <li>6. The regular sensor could not be used with Emgergy Driver at the same time. If the sensor should be worked with Emergency Driver at the same time, please ask for a special type.</li> <li>Installation instruction:</li> </ul>	EU- Standard brown blue	black — white — green —		L L N N	Pink	DIM-		D+ D+ D- D-

The safety rope is not included, if necessary 1 please purchase from the seller and clarify the length. 2

100W/150W/200W/ 240W300W400W

500W/600W

